
OSIRIS

Optical, Spectroscopic, and Infrared Remote Imaging System

OSIRIS camera bad pixel list

RO-RIS-MPAE-TN-080

Issue: 1

Revision: a

22/02/2017

Prepared by:

G. Kovacs



Approval Sheet

Prepared by: G. Kovacs (signature/date)

Approved by: H. Sierks (signature/date)



OSIRIS

Reference: **RO-RIS-MPAE-TN-080**
Issue: 1 Rev.: a
Date: 22/02/2017
Page: 3

Document Change Record



Table of contents

1	General aspects.....	5
1.1	Scope	5
1.2	Introduction	5
1.3	Applicable Documents	5
1.4	Reference Documents	5
2	Bad pixel list.....	6
2.1	Correction method.....	6
2.2	NAC bad pixels	6
2.3	WAC bad pixels	6
3	Calibration files used by OsiCalliope.....	6

List of Figures

List of Tables



1 General aspects

1.1 Scope

This document describes the current bad pixel list of the OSIRIS NAC and WAC.

1.2 Introduction

The OSIRIS cameras are built with a 2048x2048 high quality scientific CCD. These devices may contain blemishes, which must be corrected during the image calibration process. Bad pixels are produced:

- during the manufacturing of the detector
- during integration of the camera system
- in-flight

1.3 Applicable Documents

no.	document name	document number, Iss./Rev.
AD1	OSIRIS Experiment Data Record and Software Interface Specification (EDR/SIS)	RO-RIS-MPAE-ID-018
AD2	Rosetta-OSIRIS to Planetary Science Archive Interface Control Document	RO-RIS-MPAE-ID-015

1.4 Reference Documents

no.	document name	document number, Iss./Rev.
RD1	OSIRIS user manual	RO-RIS-MPAE-UM-004, D/s
RD2	OSIRIS Calibration Report	RO-RIS-MPAE-RP-147, D/b
RD3	OSIRIS Calibration Pipeline OsiCalliope	RO-RIS-MPAE-MA-007, 1/-



2 Bad pixel list

2.1 Correction method

The bad pixels are corrected by replacing their DN values by the median (or average) of the neighboring good ones. Lines or clusters can also be corrected by shifting their DN values to match the adjacent line or cluster. Details on the correction methods can be found in [RD3].

2.2 NAC bad pixels

The current bad pixels list is in effect from 2014-01-01.

Bad pixels and correction methods

None

Bad columns and correction methods

994, SHIFT_L_CORR

996, SHIFT_R_CORR

995, MEDIAN_CORR

Bad rectangular regions and methods (x₀, y₀, h, w)

915, 970, 20, 20 NO_CORR

Column 995 is a bad column, with further effect on the neighboring columns (C994 and C996). The method first corrects columns 994 and 996 by shifting their values to match in average with C993 and C997. Column 995 is then corrected by replacing each of its pixels DN with the median of 6 neighboring column pixels.

The NAC “blob” area is a rectangular area with effectively higher (dark) noise. This is marked in the image quality map, but currently not corrected.

2.3 WAC bad pixels

The current bad pixels list is in effect from 2014-01-01.

Bad pixels and correction methods

None

Bad columns or clusters and correction methods

119, 1664 MEDIAN_CORR

Bad rectangular regions and methods (x₀, y₀, h, w)

None

The WAC has one bad cluster at column 119, for line 1664 and larger.

3 Calibration files used by OsiCalliope

The calibration files used by OsiCalliope to calibrate OSIRIS images are:



-
- NAC_FM_BAD_PIXEL_V01.TXT
 - WAC_FM_BAD_PIXEL_V01.TXT

Previous versions:

- NAC_FM_BAD_PIXEL_LIST.LBL (obsolete, same values as NAC_FM_BAD_PIXEL_V01.TXT)
- WAC_FM_BAD_PIXEL_LIST.LBL (obsolete, same values as WAC_FM_BAD_PIXEL_V01.TXT)